



## Waveguide to 2.4 mm Coax Adaptors

Series 093-TF/TM

### Features

- Male and Female Connectors Available
- Models up to 50 GHz
- Full Band and Narrow Band Models

The Series 093-TF/TM Waveguide to Coax Adaptors feature an improved mechanical design offering greater durability and reliability.

The Adaptors are fitted with 2.4 mm male or female coaxial connectors which are suitable for operation over full waveguide bands up to 50 GHz.

Models optimised for limited and narrowband applications are also available to special order.

**Full details on request.**



Model 21093-TF30

Model	Frequency Range (GHz)	Waveguide			VSWR (better than)
		WG	R	WR	
19093-TF30	14.5 - 22.0	19	180	51	1.25
19093-TM30	14.5 - 22.0	19	180	51	1.25
20093-TF30	17.6 - 26.7	20	220	42	1.20
20093-TM30	17.6 - 26.7	20	220	42	1.20
21093-TF30	21.7 - 33.0	21	260	34	1.25
21093-TM30	21.7 - 33.0	21	260	34	1.25
22093-TF30	26.4 - 40.1	22	320	28	1.25
22093-TM30	26.4 - 40.1	22	320	28	1.25
23093-TF30	33.0 - 50.1	23	400	22	1.40
23093-TM30	33.0 - 50.1	23	400	22	1.40
23093-TF31	40.0 - 50.0	23	400	22	1.20
23093-TM31	40.0 - 50.0	23	400	22	1.20

### ORDERING INFORMATION

Model: Adaptor type suffix; Description

Example: Model 22093-TF30 Waveguide to 2.4 mm female coax adaptor

Series 093-TF/TM

### FLANN MICROWAVE LTD.

Dunmere Road  
Bodmin  
Cornwall  
PL31 2QL

### GET IN TOUCH:

Tel: +44 (0)1208 77777  
sales@flann.com  
www.flann.com